**OSRAM**

# LEDinspect WIRE-FREE PRO 600

**Wire-Free charging compatible**
Simply place on the Wire-Free charging pad to securely hold and recharge

**600 Lumens**
Place bright, 5700k white light where you need it most

**Built to last**
IK08 and IP54 rated to survive the rigors of the professional workshop

The easiest way to recharge inspection lights
Inspection lights are a vital part of any professional's toolbox. Removing the need to find and plug into the correct charging cable, OSRAM's wire-free inspection lights recharge without hassle by simply being placed on the magnetic charging pad. This innovative design not only enhances convenience but also supports an uninterrupted workflow.

### Technical data

| | Product information | General Product Information | Electrical Data | |
|---|---|---|---|---|
| **Product description** | **Application (Category and Product specific)** | **Global order reference** | **Nominal wattage** | **Nominal voltage** |
| INSPECTION LAMP | LED inspection lights | LEDIL421 | 5 W | 3.7 V |

| | Photometric Data | | | Physical Attributes & Dimensions |
|---|---|---|---|---|
| **Product description** | **Color temperature** | **Nominal luminous flux** | **Light color LED** | **Product weight** |
| INSPECTION LAMP | 5700 K | 600 lm | White | 300.00 g |

| | | | | Lifetime Data |
|---|---|---|---|---|
| **Product description** | **Length** | **Width** | **Height** | **Guarantee** |
| INSPECTION LAMP | 205.0 mm | 55.0 mm | 45.0 mm | 2 years |

| | Capabilities | Logistical data | Environmental & Regulatory Information Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACh) | |
|---|---|---|---|---|
| **Product description** | **Technology** | **Watt hour per battery** | **Candidate list substance 1** | **CAS No. of substance 1** |
| INSPECTION LAMP | LED | 9.62 | Lead | 7439-92-1 |

| **Product description** | **Safe use instruction** | **Declaration no. in SCIP database** |
|---|---|---|
| INSPECTION LAMP | The identification of the Candidate List substance is sufficient to allow safe use of the article. | 26c8b24d-65fc-44be-938d-14097cb7f78a |

---

## Download Data

| | File |
|---|---|
| | User instruction<br>LEDinspect WIRE-FREE PRO 600 |

**Application advice**

For more detailed application information and graphics please see product datasheet.

**Disclaimer**

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.

—